

## 9448 Wired 7 zone control panel



### Easy to install, saving you time and money

Simple wiring configuration.  
Easy to programme.

### Upgradeable to a communicating system for extra security

Option to add SD1, TSD2 and SD-GSM speech dialler to create a communicating system.

### Easy to operate

Each system has full and part set facilities, the ability to change access codes and remote keypads to give a high level of security and total peace of mind.

### Designed to offer exceptional value for money

Ideal choice for low security risk applications.

### At a glance...

- Up to six zones of protection plus exit/entry Zone (plus one dedicated entry/exit zone)
- Global tamper
- Bell, strobe and one programmable output
- Ten event log
- Day system status LED
- Communication output



Powering Business Worldwide

## Product specification

<b>Zones</b>	7 closed circuit (zone 7 pre-programmed as entry/exit)
<b>Zone Attributes</b>	Personal attack, normal alarm, chime, omit, not used, part set omit, fire, entry route
<b>Panel</b>	9448EUR-90 endstation control panel with onboard tactile illuminated rubber keypad
<b>Keypads</b>	Accepts up to 2 remote 9427 Style keypads. Dual key personal attack (PA)
<b>Display</b>	10 LED indicators on the control panel, including day (unset) LED
<b>Anti-tamper circuits</b>	Global
<b>Event Log</b>	10 events recorded
<b>Expansion</b>	No
<b>Full/part set</b>	Fully programmable part set option
<b>Panel siren</b>	Yes
<b>Internal Sounder</b>	Accepts 1 x 16 ohm internal sounder
<b>Outputs</b>	Bell and strobe 500mA open collector. 1 programmable 100mA as PIR set latch or shock sensor reset
<b>Bell duration</b>	Programmable up to 20 minutes
<b>Entry/exit times</b>	5 programmable entry and exit times
<b>Battery</b>	2.1Ah lead acid gel type rechargeable
<b>12v power</b>	Quiescent Panel: 55mA Keypad: 20mA
<b>Aux DC power</b>	500mA @ 13.8v
<b>Dimensions</b>	Control panel (H x W x D): 212 x 212 x 68mm. Keypad (H x W x D): 100 x 120 x 28mm
<b>Weight</b>	Control panel: 1.2kg
<b>Temperature range</b>	-10°C to +55°C
<b>Communication output</b>	Personal attack (PA) and burg (for speech diallers only)
<b>Compatibles</b>	Control panel operates with all types of detectors, bells and sirens
<b>Scantronic compatible equipment</b>	09427EUR-80 remote keypad, 9040 16 ohm internal siren, SD1, xcel PIR detector



**Eaton**  
Electrical Sector EMEA  
Route de la Longeraie 7  
1110 Morges, Switzerland

**Eaton**  
Security House,  
Vantage Point Business Village,  
Mitcheldean, Gloucestershire  
GL17 0SX

**Tel:** +44 (0)1594 545 400  
**Fax:** +44 (0)1594 545 401  
**Email:** securitysales@eaton.com  
**Web:** www.touchpoint-online.com