

## DS-1006KI Series Keyboard



### Features and Functions

- 128 x 64 screen
- 4-axis joystick
- Connectable to the Multi-functional Video Center (MVC) and Matrix Access Gateway (VAG) by RS-422 serial port, and shortcut operation of camera/camera groups switch on video wall
- Connectable to DVR by RS-485 serial port, and operation of front panel buttons
- Connectable to dome by RS-485 serial port and realize PTZ control and picture capture by joystick operation
- 16 user accounts management: 1 admin and 15 operators
- System upgrade and import / export of configuration files by USB-flash disk



## Specifications

|                     |                        |  |
|---------------------|------------------------|--|
| Model               | DS-1006KI              |  |
| System              | LCD screen             | 128 x 64 pixel screen                      |
|                     | Joystick               | 4-axis joystick                            |
|                     | Control mode           | RS-232, RS-422, RS-485                     |
| External Interfaces | Serial interface       | 1 RS-232, 1 RS-422, 1 RS-485               |
|                     | USB interface          | 1 × USB 2.0                                |
|                     | Power supply           | 12 VDC                                     |
| General             | Consumption            | ≤ 4.5 W                                    |
|                     | Working temperature    | -10 to +55° C (14 to 131° F)               |
|                     | Working humidity       | 10% to 90%                                 |
|                     | Dimensions (W × D × H) | 435 × 193 × 110 mm (17.1 × 7.6 × 4.3 inch) |
|                     | Weight                 | ≤ 1 kg (2.2 lb)                            |

## Available Models

DS-1006KI

Distributed by



## HIKVISION®

### Headquarters

No.555 Qianmo Road, Binjiang District,  
Hangzhou 310051, China  
T +86-571-8807-5998  
overseasbusiness@hikvision.com

**Hikvision USA**  
T +1-909-895-0400  
sales.usa@hikvision.com

**Hikvision Italy**  
T +39-0438-6902  
info.it@hikvision.com

**Hikvision Singapore**  
T +65-6684-4718  
sg@hikvision.com

**Hikvision Africa**  
T +27 (10) 0351172  
sale.africa@hikvision.com

**Hikvision Europe**  
T +31-23-55-42-770  
info.eu@hikvision.com

**Hikvision France**  
T +33(0)1-85-330-450  
info.fr@hikvision.com

**Hikvision Oceania**  
T +61-2-8599-4233  
salesau@hikvision.com

**Hikvision Hong Kong**  
T +852-2151-1761

**Hikvision Middle East**  
T +971-4-8816086  
salesme@hikvision.com

**Hikvision Spain**  
T +34-91-737-16-55  
info.es@hikvision.com

**Hikvision Canada**  
T +1-909-895-0400  
sales.usa@hikvision.com

**Hikvision Russia**  
T +7-495-669-67-99  
saleru@hikvision.com

**Hikvision Poland**  
T +48-22-460-01-50  
poland@hikvision.com

**Hikvision Korea**  
T +82-31-731-8841  
sales.korea@hikvision.com

**Hikvision India**  
T +91-22-28469900  
sales@pramahikvision.com

**Hikvision UK**  
T +01628-902140  
support.uk@hikvision.com

**Hikvision Brazil**  
T +55 11 3318-0050  
Latam.support@hikvision.com