VX2200 DIGITAL SYSTEM

OPTIONAL ACCESSORIES







2 WIRE BUS

6 WIRE BU VIDEO

AUDIO & VIDEO CONCIERGE UNITS



Art.	2210A	2210V
DESCRIPTION	Digital Concierge Station	
SERIES	900 Series	
WORKING VOLTAGE	12Vdc power input	12Vdc and 20Vdc power input
AUDIO/VIDEO	Audio only	Audio and Video
MOUNTING	Desktop	
KEYPAD	Yes: 16 button keypad for programming and operational functions	
DISPLAY	2x16 character back lit LCD display	2x16 character back lit LCD display, Colour LCD TFT 3.5" screen
DIMENSIONS (mm)	208 (W) x 230 (L) x 115 (H)	384 (W) x 230 (L) x 115 (H)
INTERFACES	RS232 for PC Programming software 2X00PC and PC Concierge software 2217	
FUNCTION AND OPERATION	Audio/Video concierge station for the VX2200 digital system where a concierge operator is required. The concierge station can intercept calls made from digital panels which can then be transferred to a specific apartment and enables calls from different apartments to intercommunicate with each other. It has 3 operating modes (OFF, DAY and NIGHT mode). When in OFF mode calls made from a digital panel to an apartment will bypass the concierge and call through to the apartment directly. When in DAY mode any calls made from a digital panel will by intercepted by the concierge station first before being transferred to an apartment. When in NIGHT mode any calls specifically for the concierge can be answered by the concierge station, otherwise calls made to a specific apartment will bypass the concierge station and call directly through to the apartment.	