Accessories Art. 323/12 12Vdc Power Supply Unit

DESCRIPTION

The Art. 323/12 is a regulated power supply with mains voltage 230Vac 50/60Hz and regulated output 12Vdc.

TERMINALS	
230V -0	Mains input 230Vac 50/60Hz
+12	+12Vdc 400mA max output

PROTECTIONS

Electronic thermal fuse.

CONNECTION TO MAINS

The system must be installed by a competent engineer and in accordance with national rules in force and installation diagrams (if provided), in particular we recommend that:

- The system is connected to the mains through an **all-pole** circuit breaker which has a contact separation of at least 3mm in each pole and shall connect all poles simultaneously;
- The **all-pole circuit breaker** shall be placed for ease of access and the switch shall remain readily operable.

MOUNTING

- Remove the terminal side covers by unscrewing the retaining screws;
- Fix the power supply to a DIN rail or directly to the wall using two expansion type screws;
- Isolate the mains using the circuit breaker mentioned above then make the connections as shown on the installation diagrams; •
- Check all connections and secure the wires into the terminals;
- When all connections are made replace and fit the terminal covers with the relevant screws;
- Restore the mains.

ELECTRICAL DATA

Mains voltage: 230Vac +6% -10% 50/60Hz **Output voltage:** +12Vdc ("+12", "-") 400mA

MECHANICAL DATA

standard DIN 3 modules "A" type Box. **Dimensions:** 52,5x105x65mm

WORKING CONDITIONS

-10 +50 °C Temperature: 90% RM MAX **Humidity:** Protection degree: IP20

CUSTOMER SUPPORT

All Countries:

VIDEX ELECTRONICS S.P.A. www.videx.it - technical@videx.it Tel: +39 0734-631669 Fax: +39 0734-632475

UK Customers: VIDEX SECURITY LTD www.videxuk.com Tech Line: 0191 224 3174 Fax: 0191 224 1559

 (ϵ)

The product is CE marked demonstrating its conformity and is for distribution within all member states of the EU with no restrictions. This product follows the provisions of the European Directives 2004/108/ECC (EMC); 2006/95/ECC (LVD) and 93/68/ECC (CE marking).



